

WIRE SUSPENSION KIT ASSMEBLY INSTRUCTIONS

These instructions are to be used in conjunction with the Mr Ralph Lamp Holder Family Installation Instructions which have the full electrical installation instructions for the Threaded Lamp Holders combined with our Fergus Ring Sets. Please read through those Installation Instructions before assembling the Wire Suspension Kit with the Threaded Lamp Holder.

You will need:

- Mini Screwdriver
- Pliers
- Threaded Lamp Holder
- Suspension Wire
- Ceiling Rose with Wire Port



Step 1 – Remove grub screw from the cord grip on the top of the Threaded Lamp Holder and then unscrew and remove the cord grip.



Step 2 – Slip the small ring attached to the Suspension Wire onto the textile cord of the Threaded Lamp Holder. Screw the ring down onto the thread coming out of the top of the Lamp Holder and secure tightly.



You can connect the ring set and lamp shade onto the Threaded Lamp Holder at this point, or at the end once the fittings have been installed.

Step 3 – Loosen the grub screw in the cord grip on the Ceiling Rose and pass the textile cord up into the Ceiling Rose. Tighten the grub screw again when the textile cord is at the desired length. Insert the suspension wire into the Ceiling Rose through the wire port, this will grip the wire as it goes in. If you need to loosen the wire back out of the wire port you will need to press the wire gripper in the port up all the way to get the wire back out. Once the Textile Cord and Suspension Wire are at the correct length for the pendant installation, connect the power as per the standard Mr Ralph Lamp Holder Family Installation Instructions and put a turn in the safety stopper at the end of the wire.

