

OUTDOORS BRASS LIGHT FIXTURES**TYPE: 778(Nyx)****INSTALLATION AND USER GUIDE****GENERAL INFORMATION AND TECHNICAL CHARACTERISTICS****THESE PRODUCTS ARE MANUFACTURED IN GREECE**

- 230V/240V ~50Hz
- IP64
- Class 1
- Maximum Wattage : 40w
- The light fixture is intended for a connection with fixed wiring

GENERAL INFORMATION REGARDING SECURITY

- The installation should be carried by a competent electrician
- Before any work you should turn off the power supply
- In case the glass breaks replace it immediately

Additional technical information regarding the product please contact: Vintage Industries**Email: info@vintageindustries.co.nz****The packaging includes:**

1 light fixture

8 screws for fixing

INSTALLATION OF THE LIGHT FIXTURE

A. PLACING THE LIGHT FIXTURE ON A SUPPORT SURFACE

1. Remove the glass and cage of the light fixture by unscrewing cage
2. Using the eight holes already drilled out in the back plate, screw back plate to the wall using screws provided

B. CONNECTING THE POWER SUPPLY

1. Unscrew the x2 screws on conduit box faceplate
2. Pass the power cable through the gland
3. Connect the phase, neutral and earth conductors (brown-blue-green) to the connector block
4. With a wrench tighten the cable gland to ensure the stability of the cable and the water tightness of the light fixture

C. PLACING THE LAMP AND OPERATION

1. Place the faceplate back on to the conduit box with screws
2. Insert bulb
3. Replace the glass and cage and screw it carefully to ensure that the light fixture will remain dry
4. Turn on the power supply to the light fixture

IMPORTANT

Do not exceed the wattage (W) recommended for the light fixture.

The electric installation should take place according to existent national legalisation and standards